



Dimmer Approval List

Beachside 2 watt Amber LED Light Engine

Magnetic Low Voltage

Dimmer	Magnitude			EMCOD
	M40L12DC-AR	M60L12DC-AR	M150L12	EIC150S12AC
Lutron				
Ariadni AYLV 600P	5%-100%	5%-100%	17%-100%	12%-100%
Diva DVLV 600P	8%-100%	6%-100%	26%-100%	14%-100%
Glyder	7%-100%	4%-100%	13%-100%	10%-100%
Nova T NTLV 600	8%-100%	14%-100%	18%-100%	11%-100%
Skylark SLV 600P	8%-100%	X	23%-100%	15%-100%
Leviton				
Sureslide Illumatech	9%-100%	6%-100%	18%-100%	12%-100%
Sureslide MLV	10%-100%	7%-100%	7%-100%	3%-100%
Cooper				
Cooper Dimmer	3%-100%	5%-100%	13%-100%	10%-100%

Electronic Low Voltage

Dimmer	L.T.F.		Hatch	
	TA60WA12LED-0000	TA60WD12LEDRE-0000	RS12-60M-LED	RL12-60M-LED
Lutron				
Diva DVELV 300P	20%-100%	17%-100%	13%-100%	X
Maestro MAELV-600	X	X	X	3%-100%
Skylark SELV 300P	31%-100%	26%-100%	22%-100%	X
Vierti VTELV 600M	22%-100%	34%-100%	30%-100%	X
Legrand				
Adorne Softap 363085	X	X	10%-100%	8%-100%
H703PTUW	X	15%-100%	16%-100%	X

Pulse Width Modulation

Dimmer	Meanwell		Amperor
	LPF-16-12P	LPV-20-12	ANP105-12P1-277-060-VD
Ecolocity			
Standard LC-LF-18DIM	3%-100%	1% -100%	1%-100%
LED Touch LC-LF-8DIM	1%-100%	1% -100%	X
LED Touch Panel LC-LF-22DIM	1%-100%	1% -100%	2%-100%
Reign			
Standard	5%-100%	1% -100%	1%-100%

Beachside 3 watt LED Light Engine

Magnetic Low Voltage

Dimmer	Magnitude			EMCOD
	M40L12DC-AR	M60L12DC-AR	M150L12	EIC150S12AC
Lutron				
Ariadni AYLV 600P	4%-100%	4%-100%	12%-100%	8%-100%
Diva DVLV 600P	6%-100%	5%-100%	19%-100%	10%-100%
Glyder	4%-100%	3%-100%	12%-100%	6%-100%
Nova T NTLV 600	12%-100%	10%-100%	13%-100%	8%-100%
Skylark SLV 600P	X	X	16%-100%	11%-100%
Leviton				
Sureslide Illumatech	7%-100%	5%-100%	14%-100%	9%-100%
Sureslide MLV	8%-100%	6%-100%	5%-100%	2%-100%
Cooper				
Cooper Dimmer	2%-100%	4%-100%	12%-100%	7%-100%

Electronic Low Voltage

Dimmer	L.T.F.		Hatch	
	TA60WA12LED-0000	TA60WD12LEDRE-0000	RS12-60M-LED	RL12-60M-LED
Lutron				
Diva DVELV 300P	14%-100%	13%-100%	10%-100%	15%-100%
Maestro MAELV-600	X	X	X	1%-100%
Skylark SELV 300P	21%-100%	19%-100%	17%-100%	24%-100%
Vierti VTELV 600M	30%-100%	15%-100%	11%-100%	X
Legrand				
Adorne Softap 363085	64%-100%	59%-100%	8%-100%	5%-100%
H703PTUW	14%-100%	12%-100%	X	X

Pulse Width Modulation

Dimmer	Meanwell		Amperor
	LPF-16-12P	LPV-20-12	ANP105-12P1-277-060-VD
Ecolocity			
Standard LC-LF-18DIM	1%-100%	1%-100%	1%-100%
LED Touch LC-LF-8DIM	1%-100%	1%-100%	X
LED Touch Panel LC-LF-22DIM	1%-100%	1%-100%	1%-100%
Reign			
Standard	1%-100%	1%-100%	1%-100%

Beachside 4 watt LED Light Engine

Magnetic Low Voltage

Dimmer	Magnitude			EMCOD
	M40L12DC-AR	M60L12DC-AR	M150L12	EIC150S12AC
Lutron				
Ariadni AYLV 600P	4%-100%	3%-100%	13%-100%	7%-100%
Diva DVLV 600P	4%-100%	4%-100%	14%-100%	8%-100%
Glyder	3%-100%	2%-100%	10%-100%	5%-100%
Nova T NTLV 600	10%-100%	9%-100%	13%-100%	7%-100%
Skylark SLV 600P	4%-100%	X	13%-100%	10%-100%
Leviton				
Sureslide Illumatech	4%-100%	X	11%-100%	8%-100%
Sureslide MLV	5%-100%	4%-100%	5%-100%	2%-100%
Cooper				
Cooper Dimmer	2%-100%	5%-100%	10%-100%	5%-100%

X = Dimmer and power supply combination is not recommended / incompatible.

Electronic Low Voltage

Dimmer	L.T.F.		Hatch	
	TA60WA12LED-0000	TA60WD12LEDRE-0000	RS12-60M-LED	RL12-60M-LED
Lutron				
Diva DVELV 300P	10%-100%	10%-100%	7%-100%	12%-100%
Skylark SELV 300P	17%-100%	15%-100%	12%-100%	21%-100%
Vierti VTELV 600M	19%-100%	30%-100%	9%-100%	X
Leviton				
Sureslide 6615-P	X	X	X	19%-100%
Legrand				
Adorne Softap 363085	65%-100%	62%-100%	58%-100%	X
H703PTUW	X	X	X	X

Pulse Width Modulation

Dimmer	Meanwell		Amperor
	LPF-16-12P	LPV-20-12	ANP105-12P1-277-060-VD
Ecology			
Standard LC-LF-18DIM	1%-100%	1%-100%	1%-100%
LED Touch LC-LF-8DIM	1%-100%	1%-100%	1%-100%
LED Touch Panel LC-LF-22DIM	1%-100%	1%-100%	1%-100%
Reign			
Standard	1%-100%	1%-100%	1%-100%

Beachside 7 watt Amber Light Engine

Magnetic Low Voltage

Dimmer	Magnitude		EMCOD
	M40L12-AR	E60L12DC-KO	EIC150S12AC
Lutron			
Diva DVLV 600P	1%-100%	X	1%-100%
Glyder	1%-100%	X	1%-100%
Maestro MAELV-600	1%-100%	1%-100%	1%-100%
Nova T NTLV 600	1%-100%	X	1%-100%
Skylark SLV 600P	1%-100%	X	1%-100%
Vareo V-600	1%-100%	X	1%-100%
Leviton			
Sureslide MLV	X	X	1%-100%
Cooper			
Cooper Dimmer	X	1%-100%	1%-100%
Legrand			
Adorne Softap 363085	9%-100%	2%-100%	7%-100%
H703PTUW	10%-100%	X	X

Electronic Low Voltage

Dimmer	L.T.F.		Hatch	
	TA60WA12LED-0000	TA60WD12LEDRE-0000	RS12-60M-LED	RL12-60M-LED
Lutron				
Caseta PD-5NE	X	1%-100%	X	X
Diva DVELV 300P	2%-100%	1%-100%	1%-100%	9%-100%
Maestro MAELV-600	5%-100%	1%-100%		
Skylark SELV 300P	4%-100%	2%-100%	1%-100%	1%-100%
Vierti VTELV 600M	1%-100%	1%-100%	X	X
Leviton				
Sureslide 6615-P	X	X	X	X
Legrand				
Adorne Softap 363085	1%-100%	2%-100%	X	X
H703PTUW	5%-100%	X	X	X

X = Dimmer and power supply combination is not recommended / incompatible.

Pulse Width Modulation

Dimmer	Meanwell		Amperor
	LPF-16-12P	LPV-20-12	ANP105-12P1-277-060-VD
Ecology			
Standard LC-LF-18DIM	1%-100%	1%-100%	1%-100%
LED Touch LC-LF-8DIM	1%-100%	1%-100%	1%-100%
LED Touch Panel LC-LF-22DIM	1%-100%	1%-100%	1%-100%
Reign			
Standard	1%-100%	1%-100%	1%-100%

Beachside 11 watt Warm White Light Engine

Magnetic Low Voltage

Dimmer	Magnitude		EMCOD
	M40L12-AR	E60L12DC-KO	EIC150S12AC
Lutron			
Diva DVLV 600P	1%-100%	X	1%-100%
Glyder	1%-100%	X	1%-100%
Maestro MAELV-600	1%-100%	1%-100%	1%-100%
Nova T NTLV 600	1%-100%	X	1%-100%
Skylark SLV 600P	1%-100%	X	1%-100%
Vareo V-600	1%-100%	X	1%-100%
Leviton			
Sureslide MLV	X	X	1%-100%
Cooper			
Cooper Dimmer	X	1%-100%	1%-100%
Legrand			
Adorne Softap 363085	9%-100%	2%-100%	7%-100%
H703PTUW	10%-100%	X	X

Electronic Low Voltage

Dimmer	L.T.F.		Hatch	
	TA60WA12LED-0000	TA60WD12LEDRE-0000	RS12-60M-LED	RL12-60M-LED
Lutron				
Caseta PD-5NE	X	1%-100%	X	X
Diva DVELV 300P	2%-100%	1%-100%	1%-100%	9%-100%
Maestro MAELV-600	5%-100%	1%-100%		
Skylark SELV 300P	4%-100%	2%-100%	1%-100%	1%-100%
Vierti VTELV 600M	1%-100%	1%-100%	X	X
Leviton				
Sureslide 6615-P	X	X	X	X
Legrand				
Adorne Softap 363085	1%-100%	2%-100%	X	X
H703PTUW	5%-100%	X	X	X

Pulse Width Modulation

Dimmer	Meanwell		Amperor
	LPF-16-12P	LPV-20-12	ANP105-12P1-277-060-VD
Ecology			
Standard LC-LF-18DIM	1%-100%	1%-100%	1%-100%
LED Touch LC-LF-8DIM	1%-100%	1%-100%	1%-100%
LED Touch Panel LC-LF-22DIM	1%-100%	1%-100%	1%-100%
Reign			
Standard	1%-100%	1%-100%	1%-100%