



Dimmer Approval List

Beachside 2-Watt Amber LED Light Engine

Magnetic Low Voltage

Dimmer	Justin Inc.		Magnitude		EMCOD
	MTP-300	GL Series**	M**L12DC (12vdc)	M**L12-AR (12vac)	EIC150S12AC (12vac)
Lutron					
Ariadni AYLV 600P	X	X	5%-100%	X	12%-100%
Diva DVLV 600P	14%-100%	14%-100%	6%-100%	11%-100%	14%-100%
Glyder GLV-600	14%-100%	14%-100%	4%-100%	7%-100%	10%-100%
Nova T NTLV 600	12%-100%	12%-100%	8%-100%	11%-100%	11%-100%
Skylark SLV 600P	13%-100%	13%-100%	8%-100%	10%-100%	15%-100%
Vareo V-600	15%-100%	15%-100%	X	X	X
Leviton					
Sureslide 6613-P	11%-100%	11%-100%	7%-100%	10%-100%	3%-100%
Cooper					
Cooper Dimmer	19%-100%	19%-100%	3%-100%	11%-100%	10%-100%
**rated for 100w and 200w			**rated for 40w and 60w		

Electronic Low Voltage

Dimmer	L.T.F.		Hatch	
	TA60WA12LED (12vac)	TA60WD12LED (12vdc)	RS12-60M-LED (12vac)	RL12-60M-LED (12vac)
Lutron				
Diva DVELV 300P	20%-100%	17%-100%	13%-100%	X
Maestro MAELV-600	X	X	X	3%-100%
Skylark SELV 300P	31%-100%	26%-100%	22%-100%	X
Vierti VTELV 600M	22%-100%	34%-100%	30%-100%	X
Legrand				
Adorne Softap 363085	X	X	X	8%-100%
H703PTUW	X	15%-100%	16%-100%	X

Pulse Width Modulation

Dimmer	Meanwell		Amperor
	LPF-16-12P	LPV-20-12	ANP105-12P1-277-060-VD
Ecology			
Standard LC-LF-18DIM	3%-100%	1% -100%	1%-100%
LED Touch LC-LF-8DIM	1%-100%	1% -100%	X
LED Touch Panel LC-LF-22DIM	1%-100%	1% -100%	2%-100%
Reign			
Standard	5%-100%	1% -100%	1%-100%

Beachside 3-Watt LED Light Engine

Magnetic Low Voltage

Dimmer	Justin Inc.		Magnitude		EMCOD
	MTP-300	GL Series**	M**L12DC (12vdc)	M**L12-AR (12vac)	EIC150S12AC (12vac)
Lutron					
Ariadni AYL 600P	X	X	4%-100%	X	8%-100%
Diva DVLV 600P	9%-100%	9%-100%	5%-100%	11%-100%	10%-100%
Glyder GLV-600	11%-100%	11%-100%	3%-100%	7%-100%	6%-100%
Nova T NTLV 600	10%-100%	10%-100%	10%-100%	11%-100%	8%-100%
Skylark SLV 600P	9%-100%	9%-100%	X	10%-100%	11%-100%
Vareo V-600	12%-100%	12%-100%	X	X	X
Leviton					
Sureslide 6613-P	8%-100%	8%-100%	6%-100%	10%-100%	2%-100%
Cooper					
Cooper Dimmer	14%-100%	14%-100%	2%-100%	11%-100%	7%-100%
**rated for 100w and 200w			**rated for 40w and 60w		

Electronic Low Voltage

Dimmer	L.T.F.		Hatch	
	TA60WA12LED (12vac)	TA60WD12LED (12vdc)	RS12-60M-LED (12vac)	RL12-60M-LED (12vac)
Lutron				
Diva DVELV 300P	14%-100%	13%-100%	10%-100%	15%-100%
Maestro MAELV-600	X	X	X	1%-100%
Skylark SELV 300P	21%-100%	19%-100%	17%-100%	24%-100%
Vierti VTELV 600M	30%-100%	15%-100%	11%-100%	X
Legrand				
Adorne Softap 363085	X	X	X	5%-100%
H703PTUW	14%-100%	12%-100%	X	X

Pulse Width Modulation

Dimmer	Meanwell		Amperor
	LPF-16-12P	LPV-20-12	ANP105-12P1-277-060-VD
Ecolocity			
Standard LC-LF-18DIM	1%-100%	1%-100%	1%-100%
LED Touch LC-LF-8DIM	1%-100%	1%-100%	X
LED Touch Panel LC-LF-22DIM	1%-100%	1%-100%	1%-100%
Reign			
Standard	1%-100%	1%-100%	1%-100%

Beachside 4-Watt LED Light Engine

Magnetic Low Voltage

Dimmer	Justin Inc.		Magnitude		EMCOD
	MTP-300	GL Series**	M**L12DC (12vdc)	M**L12-AR (12vac)	EIC150S12AC (12vac)
Lutron					
Ariadni AYL 600P	X	X	3%-100%	3%-100%	7%-100%
Diva DVLV 600P	9%-100%	9%-100%	4%-100%	4%-100%	8%-100%
Glyder GLV-600	10%-100%	10%-100%	2%-100%	2%-100%	5%-100%
Nova T NTLV 600	8%-100%	8%-100%	9%-100%	9%-100%	7%-100%
Skylark SLV 600P	8%-100%	8%-100%	4%-100%	X	10%-100%
Vareo V-600	11%-100%	11%-100%	X	X	X
Leviton					
Sureslide 6613-P	7%-100%	7%-100%	4%-100%	X	2%-100%
Cooper					
Cooper Dimmer	12%-100%	12%-100%	2%-100%	5%-100%	5%-100%
**rated for 100w and 200w			**rated for 40w and 60w		

Electronic Low Voltage

Dimmer	L.T.F.		Hatch	
	TA60WA12LED (12vac)	TA60WD12LED (12vdc)	RS12-60M-LED (12vac)	RL12-60M-LED (12vac)
Lutron				
Diva DVELV 300P	10%-100%	10%-100%	7%-100%	12%-100%
Skylark SELV 300P	17%-100%	15%-100%	12%-100%	21%-100%
Vierti VTELV 600M	19%-100%	30%-100%	9%-100%	X
Leviton				
Sureslide 6615-P	X	X	X	19%-100%

Pulse Width Modulation

Dimmer	Meanwell		Amperor
	LPF-16-12P	LPV-20-12	ANP105-12P1-277-060-VD
Ecology			
Standard LC-LF-18DIM	1%-100%	1%-100%	1%-100%
LED Touch LC-LF-8DIM	1%-100%	1%-100%	1%-100%
LED Touch Panel LC-LF-22DIM	1%-100%	1%-100%	1%-100%
Reign			
Standard	1%-100%	1%-100%	1%-100%

Beachside 7-Watt Amber Light Engine

Magnetic Low Voltage

Dimmer	Justin Inc.		Magnitude		EMCOD
	MTP-300	GL Series**	M**L12-AR (12vac)	E**L12DC (12vdc)	EIC150S12AC (12vac)
Lutron					
Diva DVLV 600P	1%-100%	1%-100%	1%-100%	X	1%-100%
Glyder GLV-600	2%-100%	2%-100%	1%-100%	X	1%-100%
Maestro MAELV-600	X	X	1%-100%	1%-100%	1%-100%
Nova T NTLV 600	1%-100%	1%-100%	1%-100%	X	1%-100%
Skylark SLV 600P	1%-100%	1%-100%	1%-100%	X	1%-100%
Vareo V-600	1%-100%	1%-100%	1%-100%	X	1%-100%
Leviton					
Sureslide 6613-P	2%-100%	2%-100%	X	X	1%-100%
Cooper					
Cooper Dimmer	4%-100%	4%-100%	X	1%-100%	1%-100%
Legrand					
Adorne Softap 363085	X	X	9%-100%	X	7%-100%
H703PTUW	X	X	10%-100%	X	X
		**rated for 100w and 200w		**rated for 40w and 60w	

Electronic Low Voltage

Dimmer	L.T.F.		Hatch	
	TA60WA12LED (12vac)	TA60WD12LED (12vdc)	RS12-60M-LED (12vac)	RL12-60M-LED (12vac)
Lutron				
Caseta PD-5NE	X	1%-100%	X	X
Diva DVELV 300P	2%-100%	1%-100%	1%-100%	9%-100%
Maestro MAELV-600	5%-100%	1%-100%		
Skylark SELV 300P	4%-100%	2%-100%	1%-100%	1%-100%
Vierti VTELV 600M	1%-100%	1%-100%	X	X
Leviton				
Sureslide 6615-P	X	X	X	X
Legrand				
Adorne Softap 363085	1%-100%	2%-100%	X	X
H703PTUW	5%-100%	X	X	X

Pulse Width Modulation

Dimmer	Meanwell		Amperor
	LPF-16-12P	LPV-20-12	ANP105-12P1-277-060-VD
Ecology			
Standard LC-LF-18DIM	1%-100%	1%-100%	1%-100%
LED Touch LC-LF-8DIM	1%-100%	1%-100%	1%-100%
LED Touch Panel LC-LF-22DIM	1%-100%	1%-100%	1%-100%
Reign			
Standard	1%-100%	1%-100%	1%-100%

Beachside 11-Watt Warm White Light Engine

Magnetic Low Voltage

Dimmer	Justin Inc.		Magnitude		EMCOD
	MTP-300	GL Series**	M**L12-AR (12vac)	E**L12DC (12vdc)	EIC150S12AC (12vac)
Lutron					
Diva DVLV 600P	1%-100%	1%-100%	1%-100%	X	1%-100%
Glyder GLV-600	1%-100%	1%-100%	1%-100%	X	1%-100%
Maestro MAELV-600	X	X	1%-100%	1%-100%	1%-100%
Nova T NTLV 600	1%-100%	1%-100%	1%-100%	X	1%-100%
Skylark SLV 600P	1%-100%	1%-100%	1%-100%	X	1%-100%
Vareo V-600	1%-100%	1%-100%	1%-100%	X	1%-100%
Leviton					
Sureslide 6613-P	1%-100%	1%-100%	X	X	1%-100%
Cooper					
Cooper Dimmer	X	X	X	1%-100%	1%-100%
Legrand					
Adorne Softap 363085	X	X	9%-100%	X	7%-100%
H703PTUW	X	X	10%-100%	X	X
		**rated for 100w and 200w		**rated for 40w and 60w	

Electronic Low Voltage

Dimmer	L.T.F.		Hatch	
	TA60WA12LED (12vac)	TA60WD12LED (12vdc)	RS12-60M-LED (12vac)	RL12-60M-LED (12vac)
Lutron				
Caseta PD-5NE	X	1%-100%	X	X
Diva DVELV 300P	2%-100%	1%-100%	1%-100%	9%-100%
Maestro MAELV-600	5%-100%	1%-100%		
Skylark SELV 300P	4%-100%	2%-100%	1%-100%	1%-100%
Vierti VTELV 600M	1%-100%	1%-100%	X	X
Leviton				
Sureslide 6615-P	X	X	X	X
Legrand				
Adorne Softap 363085	1%-100%	2%-100%	X	X
H703PTUW	5%-100%	X	X	X

Pulse Width Modulation

Dimmer	Meanwell		Amperor
	LPF-16-12P	LPV-20-12	ANP105-12P1-277-060-VD
Ecology			
Standard LC-LF-18DIM	1%-100%	1%-100%	1%-100%
LED Touch LC-LF-8DIM	1%-100%	1%-100%	1%-100%
LED Touch Panel LC-LF-22DIM	1%-100%	1%-100%	1%-100%
Reign			
Standard	1%-100%	1%-100%	1%-100%